

## HIGH EFFICIENCY 30KW FM TRANSMITTER EM 30000 HE DIG PLUS

The 30KW FM transmitter **EM 30000 HE DIG PLUS** has been created by the OMB center of development for high efficiency transmitters. It consists on the FMA 30000 HE power amplifier and the EM 250 DIG PLUS transmitter. This high efficiency 30KW amplifier is composed by six 5KW amplifying units (FMA 5000 HE). This transmitter can be supplied with dual exciter and changeover.



### MAIN ADVANTAGES

- Six amplifying units, each composed by six amplifying modules of 1.200W with robust LDMOS transistors of the latest technology.
- Each amplifying unit contains three independent switching power supplies connected in parallel to maintain the equipment working in case any of them fails.
- TFT screen and touch keyboard to control and to visualize operation parameters.
- Memory recording of events.
- Speed control of cooling fans according to temperature of power modules so as to optimize consumption and to decrease acoustic contamination.
- Advanced protection against load mismatches without transmission cuts and fast protection in case of excessive reflected power and/or excessive input power.
- Analog telemetry, digital remote control and telemetry RS232, remote control by opened/closed contacts.
- Automatic power reduction at night when used in combination with the EM 250 DIG PLUS transmitter.
- Automatic power reduction in case of high temperature, the equipment returns automatically to its rated power value when the temperature reaches back an average value.
- Automatic power reduction in case of excessive reflected power.

broadcast your \_ world

## GENERAL CHARACTERISTICS

<b>AMPLIFIER FMA 30000 HE</b>	
<b>FREQUENCY RANGE</b>	87.5-108MHz
<b>INPUT RETURN LOSS</b>	-20dB
<b>INPUT POWER</b>	250W
<b>OUTPUT POWER</b>	30KW nominal, manual and automatic adjustable
<b>COOLING</b>	Forced air, speed control of fans
<b>HARMONICS LEVEL</b>	-80dBc
<b>INPUT/OUTPUT IMPEDANCE</b>	50Ω
<b>RF INPUT CONNECTOR</b>	N(F)
<b>RF OUTPUT CONNECTOR</b>	EIA 3+1/8"
<b>RF MONITOR CONNECTOR</b>	BNC(F)
<b>POWER SUPPLY</b>	Three-phase: 230VAC (without N); 380VAC (with N) ±15%, 50/60Hz
<b>TYPICAL AC EFFICIENCY</b>	70%
<b>CONSUMPTION</b>	70A per three-phase 380VAC @30KW
<b>PROTECTIONS</b>	Reflected power, forward power, overdrive, and overcurrent in power modules. Smart temperature protection. Ultra-fast protection against reflected and input power. Real time registration of events. Exciter's inhibition
<b>TELEMETRY AND REMOTE CONTROL</b>	Analog telemetry (direct and reflected power measurements). Digital telemetry and remote control RS232. Remote control by opened/closed contacts
<b>OPERATION TEMPERATURE</b>	0 to +40°C

broadcast your \_ world

<b>EXCITER EM 250 DIG PLUS</b>	
<b>FREQUENCY RANGE</b>	87.5-108MHz
<b>FM MODULATION</b>	75KHz (adjustable) peak deviation. Mono 180kF3E and Stereo 256kF3E
<b>AUDIO/MPX INPUT LEVEL</b>	-3.5 @ +12.5dBm @ 75KHz deviation
<b>AUDIO INPUT CONNECTORS</b>	XLR(F)
<b>AUXILIARY CHANNEL (RDS/SCA) INPUT LEVEL</b>	7.5KHz deviation: -12.5 to 3.5dBm and 2KHz deviation: -24 to -8dBm
<b>AUX. CHANNEL INPUT IMPEDANCE</b>	10kOhm
<b>MODULATION DISTORTION</b>	7.5KHz deviation: <0.05%, 0.02% typical; 2KHz deviation: <0.2%, 0.05% typical
<b>S/N MONO RATIO</b>	30 to 20000Hz: >76dB, 86dB typical, CCIR: >75dB, 81dB typical
<b>S/N STEREO RATIO</b>	30 to 20000Hz: >72dB, 77dB typical, CCIR: >68dB, 72dB typical
<b>AUDIO CHANNELS BANDWIDTH</b>	30 to 15000Hz $\pm$ 0.1dB
<b>PRE-EMPHASIS TIME CONSTANT</b>	Selectable, 25/50/75 microseconds
<b>RF NOMINAL OUTPUT POWER</b>	250W
<b>TUNING STEPS OF TRANSMITTER</b>	10/100KHz
<b>ALC OUTPUT POWER STABILITY</b>	$\pm$ 3%
<b>SPURIOUS AND HARMONIC EMISSIONS</b>	<80dBc
<b>RF OUTPUT IMPEDANCE</b>	50 $\Omega$
<b>RF INPUT POWER CONNECTOR</b>	N
<b>RF SAMPLING CONNECTOR</b>	BNC
<b>POWER SUPPLY</b>	110-230Vac $\pm$ 15% 50-60Hz
<b>CONSUMPTION</b>	460VA (250W)
<b>OPERATION TEMPERATURE RANGE</b>	0 to 40°C recommended, -10 to 55°C max.
<b>RELATIVE HUMIDITY</b>	Up to 95% without condensation

*\* The images and/or technical specifications are subject to change without previous notice.*

broadcast your \_ world