

Opera plus Family

A07 b

EcoLine

Fully digital

- o on um tion
 oney a ing

7U



The picture is for illustrative purposes

Il trasmettitore OPERA FM 87,5÷108MHz da 5000W utilizza 6 pallet da 1400W LDMOS di 6^a generazione a larga banda con protezione ROS 65:1 e 3 Alimentatori estraibili da pannello frontale.

L'ingegnerizzazione adottata garantisce un elevato risparmio in termini di consumo energetico (tra i più bassi della categoria) e di trasporto grazie alle ridotte dimensioni ed al peso contenuto. L'installazione è facile e veloce. La semplicità d'utilizzo unita ad una manutenzione veramente molto ridotta rende questi trasmettitori ideali per stazioni non sorvegliate.

Caratteristiche:

- Amplificatori RF larga banda con tecnologia LD-Mos
- AAQ Advanced Audio Quality, per la migliore qualità audio
- Elenco eventi consultabile da display o interfaccia WEB
- Modulatore con sintetizzatore di frequenza digitale.
- Automatic Audio change-over / L+R, MPX or Mixed
- Protezione contro aumento del ROS di antenna con riduzione automatica della potenza di uscita (fold-back)
- Protezione di temperatura con riduzione di potenza (fold-back)
- Display LCD per controllo dei principali parametri
- 6 ampl. 1400W per la massima affidabilità su unico radiatore
- 3 Alimentatori (3500VA SMPS) estraibili a commutazione per la massima affidabilità ed efficienza
- Aria di raffreddamento canalizzata
- 2 ventilatori facilmente sostituibili
- Filtro delle armoniche e accoppiatore direzionale incorporati
- Rack da 19" da 7 Unità
- Telemetria GSM, TCP/IP, SNMP & SMTP - Presa Cuffie
- Moduli Plug&Play facilmente sostituibili

OPERA 5000W FM 87,5÷108MHz transmitter uses 6x1400W pallet with 6^a generation LDMOS technology, 65:1 VSWR and 3x3500W Hot Pluggable Power Supplies.

The technical solutions adopted by our engineers are focused to assure energy saving (among the lowest) and high reliability. Settings, protections, telemetry are totally microprocessor controlled. The installation and the maintenance of the equipment are respectively very fast and easy. These fully protected transmitters are indicated for use in unmanned stations.

Features:

- Wideband circuits amplifiers with LD-Mos technology
- AAQ: Advanced Audio Quality
- Storage of events
- Built-in Fully digital controlled Modulator.
- Automatic Audio change-over / L+R, MPX or Mixed
- Automatic fold-back ROS & Temperature protection
- Ambient & RF Module temperature measurement
- 4 lines LCD alphanumeric display
- 6x1400W ampli. in only one heat-sink for the highest reliability
- 3x3500VA HOT PLUGGABLE Power Supply with PFC
- Sealed duct cooling air with blowers
- 2 External easy removable blowers
- Harmonics filter & directional coupler built-in
- 7 unit 19" standard rack
- GSM Telemetry TCP/IP Webserver, SNMP & SMTP server.
- Front panel Headphone jack for audio monitor
- Plug&Play Modules - easily replaceable
- Metals treated with galvanic process



Trasmettitore FM W Integrato FM Integrated Transmitter



Options :

- Digital Stereo Encoder Module
- RDS encoder
- AES-EBU digital audio input / Audio from IP
- Input & Output special dry contacts
- Bidirectional remote control by GSM/SMS
- Remote control by TCP-IP/WebServer/SNMP-SMTP
- Remote control by RS-232



er Amplifier Secti n

Specifications are subject to change without notice.

General specification

Operating voltage	400VAC $\pm 15\%$ 3phas 230VAC $\pm 10\%$ Monopha > 71%
Typical Efficiency	Forced air
Cooling	up to 4000m (13123 ft) over sl
Operating altitude	<
Typical Consumption	-5° to 50°C
Operational temperature range	-20° to 60°C
Storage temperature range	EIA 7/8"
Output RF connector	BNC
Monitor RF connector	485x310,8x625mm / 60Kg
Dimensions	

www.tem-italy.it

Radio frequency

Frequency range	87.5 to 108MHz
Frequency setting	in 10KHz or 100 KHz steps
Setting mode	By keys on the front panel/Remote
Frequency stability	< $\pm 300\text{Hz/year}$ - 0.5ppm*
Frequency generation	PLL synthesizer
Modulation type	direct VCO frequency modul. F3
Nominal frequency deviation	$\pm 75\text{KHz}$
Deviation linearity in all freq. range	$\pm 5\text{KHz}$
RF output power	5000 W $\pm 0.3\text{dB}$ - Adjustable
Internal Driver power	max 10W
Harmonics emission	< -70dBc*

Modulation capability

MONO (left and right)
L-R & AES-EBU
SCA + RDS
Composite
IP Audio

MPX characteristics

Signal input	MPX
Composite Input impedance	10Kohm unbalanced
Input connector	BNC
Input level	Adjustable 0/+6/Variable
Audio freq. response (30Hz to 60KHz)	< 0,5 dB
Modulation distortion	< 0.1%
Signal to noise ratio	> 75dB

Stereo characteristics

Signal inputs	Left or Right - AES-EBU
Input impedance	600ohm (bal.) or 10k ohm
Input connectors	Canon XLR
Unbalanced rejection	> 40dB
Input level	Adjustable (Front/Remote)
Pre- emphasis	75 or 50uS
Audio frequency response (30Hz to 15KHz)	< 0.25dB
Audio frequency response (19KHz to 100KHz)	> 50dB
Cross-talk between left and right channel	> 50dB
Distortion at frequency deviation of 75KHz	< 0.1%
Signal to noise referred at deviation of 75KHz	> 75dB
Suppression of 38KHz	> 50dB

